Spectrum™ Technology Platform
Version 12.1 S06

Spectrum™ Technology Platform Release Notes

This document contains information about Spectrum™ Technology Platform 12.1 S06. You have access only to the modules you have licensed. To evaluate any other modules, contact your Pitney Bowes account executive for a trial license key.

Who should apply this update?	This product update is intended for Spectrum Technology Platform 12.1 users.
Is this update required?	This product update is not required.

Contents:

Fixed Issues 2
Installation 2

Fixed Issues

Subflow inspection drill-down input error

(CDQE-61834) - When a subflow was exposed and used multiple times as stages in a dataflow, the inspection on the dataflow was correct. However, if the user selected the exposed stage, then chose "Inspect this Dataflow" to drill-down into the subflow, the input data passed into the subflow remained the same, which was incorrect.

Execution history date-time format

(CDQE-61026) - Execution history process flow Started and Finished date-time format error: In Enterprise Designer, the process flow execution history would show started/finished date and time in U.S. format, only.

Installation

To install this product update you must have Spectrum™ Technology Platform 12.1 installed.

Important: Before you install this product update, be sure that you have installed all previously-released product updates for your modules and the platform. Unexpected issues may occur if you do not install product updates in the proper order. For a listing of product updates for each module and the platform, see the **Product Update Summary** on **support.pb.com/spectrum**.

Applying this product update to a cluster

To apply this product update to a cluster, install the product update to each node by following the instructions in these release notes. You can apply the product update to one node at a time without stopping all the nodes in the cluster.

Installing on Windows

Note: In this procedure, *SpectrumDirectory* refers to the folder where you have installed the Spectrum™ Technology Platform server.

1. Stop the Spectrum™ Technology Platform server. To stop the server, right-click the Spectrum™ Technology Platform icon in the Windows system tray and select **Stop Spectrum™**. Alternatively, you can use the Windows Services control panel and stop the Pitney Bowes Spectrum™ Technology Platform service.
2. Back up these files to different locations:

   SpectrumDirectory`\server\app\exports\client-12.1-ED.zip`
   SpectrumDirectory`\server\app\exports\client-12.1-Common.zip`

3. Download the zip file containing the patch from **www.g1.com/support**.
4. Extract the contents of the zip file to a temporary location.
5. Extract the resulting zip file (`cdq1210S06.zip`) to the folder where you installed Spectrum. For example, `C:\Program Files\Pitney Bowes\Spectrum`.

   Choose to overwrite the existing files.

6. Be sure to delete `%TEMP%\g1Assemblies` on the Enterprise Designer client machine *before* running Enterprise Designer.
7. Start the Spectrum™ Technology Platform server. To start the server, right-click the Spectrum™ Technology Platform icon in the Windows system tray and select **Start >Spectrum™**. Alternatively, you can use the Windows Services control panel to start the Pitney Bowes Spectrum™ Technology Platform service.

Installing on Unix or Linux

Note: In this procedure, *SpectrumDirectory* refers to the directory where you have installed the Spectrum™ Technology Platform server.

1. Source the *SpectrumDirectory*`/server/bin/setup` script.
2. Run the *SpectrumDirectory*`/server/bin/server.stop` script to stop the Spectrum™ Technology Platform server.
3. Back up these files to different locations:

   SpectrumDirectory`\server\app\exports\client-12.1-ED.zip`
   SpectrumDirectory`\server\app\exports\client-12.1-Common.zip`

4. Download the zip file containing the patch from **www.g1.com/support** and extract the contents to a temporary location.
5. FTP the `cdq1210S06.tar` file in binary mode to a temporary directory on the Spectrum™ Technology Platform machine.
6. Change to the directory where Spectrum™ Technology Platform is installed.
7. Be sure to delete `%TEMP%\g1Assemblies` on the Enterprise Designer client machine *before* running Enterprise Designer.
8. Untar the file using this command:

   `tar -xvf` *`TemporaryDirectory`*`/cdq1210S06.tar`
9. Run the *`SpectrumDirectory`*`/server/bin/server.start` script to start the Spectrum™ Technology Platform server.

3001 Summer Street
Stamford CT 06926-0700
USA

www.pitneybowes.com

© 2017 Pitney Bowes Software Inc.
All rights reserved