



Spectrum Technology Platform

Version 2022.1.0 S10

Release Notes

This document contains information about Spectrum Technology Platform 2022.1.0 S10. You have access only to the modules you have licensed. To evaluate any other modules, contact your Precisely account executive for a trial license key.

Who should apply this update?	This product update is for users of the Spectrum Technology Platform 2022.1 Spatial product.
--------------------------------------	--

Is this update required?	This product update is mandatory for Spatial and Spectrum Spatial Analyst users only.
---------------------------------	---

Contents:

Fixed Issues	2
Installation.....	2



Fixed Issues

This release contains the following Spectrum Spatial fix:

Bug ID	Description
SSS-19106	Upgraded Apache Commons Text to 1.10.0 to fix the security vulnerabilities.

Installation

To install this product update, you must have Spectrum Technology Platform 2022.1.0 installed.

Important:

Before you install this product update, be sure that you have installed all previously released product updates for your modules and the platform. Unexpected issues may occur if you do not install product updates in the proper order.

For a listing of product updates for each module and the platform, see the [Product Update Summary](#)

Applying This Product Update to a Cluster

To apply this product update to a cluster, install the product update to each node by following the instructions in these release notes. You can apply the product update to one node at a time without stopping all the nodes in the cluster.

Installing on Windows

Note: In this procedure, *SpectrumFolder* is the folder where you have installed the Spectrum Technology Platform server.

1. Ensure that all Spectrum applications are closed.
2. Stop the Spectrum Technology Platform server.

- To stop the server, right-click the Spectrum Technology Platform icon in the Windows system tray and select **Stop Spectrum**.
 - Alternatively, you can use the Windows Services control panel and stop the **Spectrum Technology Platform** service.
3. Back up the following file to a different location:

```
SpectrumFolder\server\deploy\SpatialServerManager.war
```
 4. Click the link in the release announcement to download the ZIP file containing the product update. You can download the software and release notes from the [2022.1.0 Updates](#) page.
 5. Extract the contents of the resulting ZIP file (`cdq20221s10.zip`) to the folder where you have installed the Spectrum Technology Platform server (*SpectrumFolder*).
Choose to overwrite the existing files.
 6. Start the Spectrum Technology Platform server.
 - To start the server, right-click the Spectrum Technology Platform icon in the Windows system tray and select **Start Spectrum**.
 - Alternatively, you can use the Windows Services control panel to start the **Spectrum Technology Platform** service.

The amount of time it takes to restart the Spectrum Technology Platform server will depend on your installation.

Installing on Linux

Note: In this procedure, *SpectrumDirectory* is the directory where you have installed the Spectrum Technology Platform server.

1. Ensure that all Spectrum applications are closed.
2. Stop the Spectrum Technology Platform server.
 - Source the *SpectrumDirectory*/server/bin/setup script.
 - Run the *SpectrumDirectory*/server/bin/server.stop script to stop the Spectrum Technology Platform server.
3. Back up the following file to a different location:

```
SpectrumFolder/server/deploy/SpatialServerManager.war
```
4. Click the link in the release announcement to download the ZIP file containing the product update. You can download the software and release notes from the [2022.1.0 Updates](#) page.
5. Extract the contents of the ZIP file to a temporary location.

6. FTP the `cdq20221s10.tar` file in binary mode to a temporary directory on the Spectrum Technology Platform machine.
7. Change to the directory where Spectrum Technology Platform is installed (*SpectrumDirectory*).
8. Untar the file using this command:

```
tar -xvf TemporaryDirectory/cdq20221s10.tar
```
9. Run the *SpectrumDirectory/server/bin/server.start* script to start the Spectrum Technology Platform server.

The amount of time it takes to restart the Spectrum Technology Platform server will depend on your installation.



1700 District Ave Ste 300
Burlington MA 01803-5231
USA

www.precisely.com

Copyright 2007, 2022 Precisely