

Spectrum™ Technology Platform

Version 2018.2 S16

Release Notes

This document contains information about Spectrum™ Technology Platform 2018.2 S16. You have access only to the modules you have licensed. To evaluate any other modules, contact your Pitney Bowes account executive for a trial license key.

Who should apply this update? This product update is intended for the users of Universal Addressing Module's Loqate.

Is this update required? This product update is mandatory.

Contents:

What's New	2
Installation	2

What's New

Transaction Tracker for Loqate

(CDQE-74411) Implementation of *Loqate* transaction tracker.

Loqate now charges on the basis of *number of valid records processed*, the product update **2018.2 S16** provides you with a transaction tracker which helps you track the transactions processed by loqate.

Installation

To install this product update you must have Spectrum™ Technology Platform release 2018.2 installed.

Important: Before you install this product update, be sure that you have installed all previously-released product updates for your modules and the platform. Unexpected issues may occur if you do not install product updates in the proper order. For a listing of product updates for each module and the platform, see the [Product Update Summary](https://support.pb.com/spectrum) on support.pb.com/spectrum.

Applying this product update to a cluster

To apply this product update to a cluster, install the product update to each node by following the instructions in these release notes. You can apply the product update to one node at a time without stopping all the nodes in the cluster.

Installing on Windows

Note: In this procedure, *SpectrumLocation* refers to the folder where you have installed the Spectrum™ Technology Platform server.

1. Stop the Spectrum™ Technology Platform server. To stop the server, right-click the Spectrum™ Technology Platform icon in the Windows system tray and select **Stop Spectrum™**. Alternatively, you can use the Windows Services Control Panel and stop the Pitney Bowes Spectrum™ Technology Platform service.

2. Back up this file to a different location:

```
<SpectrumLocation>\server\app\deploy\loqate-18.2.car
```

3. Download the *.zip* file containing the patch.
4. Extract the contents of the zip file to a temporary location.
5. Extract the resulting zip file (*cdq20182s16.zip*) to the folder where you installed Spectrum. For example, *C:\Program Files\Pitney Bowes\Spectrum*.

Choose to overwrite the existing files.

6. Start the Spectrum™ Technology Platform server. To start the server, right-click the Spectrum™ Technology Platform icon in the Windows system tray and select **Start Spectrum™**. Alternatively, you can use the Windows Services Control Panel to start the Pitney Bowes Spectrum™ Technology Platform service.

Installing on Unix or Linux

In this procedure, *SpectrumLocation* refers to the directory where you have installed the Spectrum™ Technology Platform server.

1. Source the *SpectrumLocation/server/bin/setup* script.
2. Back up this file and folder to a different location:

```
<Spectrumlocation>/server/app/deploy/loqate-18.2.car
```

3. Run the *SpectrumLocation/server/bin/server.stop* script to stop the Spectrum™ Technology Platform server.
4. Download the zip file containing the patch, and extract the contents to a temporary location.
5. FTP the *cdq20182s16.tar* file in binary mode to a temporary directory on the Spectrum™ Technology Platform machine.
6. Untar the file using this command:

```
tar -xvf TemporaryDirectory/cdq20182s16.tar
```

7. Run the *SpectrumLocation/server/bin/server.start* script to start the Spectrum™ Technology Platform server.



3001 Summer Street
Stamford CT 06926-0700
USA

www.pitneybowes.com